

**NAME**

fbdev – video driver for framebuffer device

**SYNOPSIS**

**Section "Device"**

**Identifier** "*devname*"

**Driver** "fbdev"

**BusID** "*pci:bus:dev:func*"

...

**EndSection**

**DESCRIPTION**

**fbdev** is an Xorg driver for framebuffer devices. This is a non-accelerated driver, the following framebuffer depths are supported: 8, 15, 16, 24. All visual types are supported for depth 8, and TrueColor visual is supported for the other depths. Multi-head configurations are supported.

**SUPPORTED HARDWARE**

The **fbdev** driver supports all hardware where a framebuffer driver is available. fbdev uses the os-specific submodule fbdevhw(4) to talk to the kernel device driver. Currently a fbdevhw module is available for linux.

**CONFIGURATION DETAILS**

Please refer to xorg.conf(5) for general configuration details. This section only covers configuration details specific to this driver.

For this driver it is not required to specify modes in the screen section of the config file. The **fbdev** driver can pick up the currently used video mode from the framebuffer driver and will use it if there are no video modes configured.

For PCI boards you might have to add a BusID line to the Device section. See above for a sample line.

The following driver **Options** are supported:

**Option "fbdev" "*string*"**

The framebuffer device to use. Default: /dev/fb0.

**Option "ShadowFB" "*boolean*"**

Enable or disable use of the shadow framebuffer layer. Mandatory for 24bpp framebuffers on newer servers. Default: on.

**Option "Rotate" "*string*"**

Enable rotation of the display. The supported values are "CW" (clockwise, 90 degrees), "UD" (upside down, 180 degrees) and "CCW" (counter clockwise, 270 degrees). Implies use of the shadow framebuffer layer. Disabled for 24bpp framebuffers. Default: off.

**SEE ALSO**

Xorg(1), xorg.conf(5), Xserver(1), X(7), fbdevhw(4)

**AUTHORS**

Authors include: Gerd Knorr, Michel Dänzer, Geert Uytterhoeven