



**Full credit is given to the above companies including the Operating System (OS) that this PDF file was generated!**

### ***Rocky Enterprise Linux 9.2 Manual Pages on command 'ciptool.1'***

***\$ man ciptool.1***

CIPTOOL(1)                      Linux System Administration                      CIPTOOL(1)

#### NAME

ciptool - Bluetooth Common ISDN Access Profile (CIP)

#### SYNOPSIS

ciptool [OPTIONS] COMMANDS

#### DESCRIPTION

ciptool(1) is used to set up, maintain, and inspect the CIP configuration of the Bluetooth subsystem in the Linux kernel.

#### OPTIONS

-i <hciX|BDADDR>

The command is applied to device hciX , which must be the name or the address of an installed Bluetooth device.

If not specified, the command will be use the first available Bluetooth device.

-h, --help

Show help options

#### COMMANDS

show Display information about the connected devices.

search Search for Bluetooth devices and connect to first one that offers CIP support.

connect <BDADDR> [PSM]

Connect the local device to the remote Bluetooth device on the specified PSM number. If no PSM is specified, it will use the SDP to retrieve it from the remote device.

release [BDADDR]

Release a connection to the specific device. If no BDADDR is given and only one device is connected this will be released.

loopback <BDADDR> [PSM]

Create a connection to the remote device for Bluetooth testing. This command will not provide a CAPI controller, because it is only for testing the CAPI Message Transport Protocol.

## RESOURCES

<http://www.bluez.org>

## REPORTING BUGS

[linux-bluetooth@vger.kernel.org](mailto:linux-bluetooth@vger.kernel.org)

## AUTHOR

Marcel Holtmann <[marcel@holtmann.org](mailto:marcel@holtmann.org)>

## COPYRIGHT

Free use of this software is granted under the terms of the GNU Lesser General Public License (LGPL).

BlueZ

June 3, 2003

CIPTOOL(1)