



Rocky Enterprise Linux 9.2 Manual Pages on command 'tc-ife.8'

C:\>man tc-ife.8

IFE action in tc(8) Linux IFE action in tc(8)

NAME

IFE - encapsulate/decapsulate metadata

SYNOPSIS

```
tc ... action ife DIRECTION [ ACTION ] [ dst DMAC ] [ src SMAC ] [ type TYPE ] [
CONTROL ] [ index INDEX ]
```

DIRECTION := { decode | encode }

ACTION := { allow ATTR | use ATTR value }

ATTR := { mark | prio | tcindex }

CONTROL := { reclassify | use | pipe | drop | continue | ok | goto chain CHAIN_IN?
DEX }

DESCRIPTION

The `ife` action allows for a sending side to encapsulate arbitrary metadata, which is then decapsulated by the receiving end. The sender runs in encoding mode and the receiver in decode mode. Both sender and receiver must specify the same ethertype.

In the future, a registered ethertype may be available as a default.

OPTIONS

`decode` For the receiving side; decode the metadata if the packet matches.

`encode` For the sending side. Encode the specified metadata if the packet matches.

`allow` Encode direction only. Allows encoding specified metadata.

`use` Encode direction only. Enforce static encoding of specified metadata.

`mark [u32_value]` The value to set for the `skb` mark. The `u32` value is required only when `use` is specified. If mark value is zero, it will not be encoded, instead "overlimits" statistics increment and `CONTROL` action is taken.

`prio [u32_value]` The value to set for priority in the `skb` structure. The `u32` value is required only when `use` is specified.

`tcindex [u16_value]` Value to set for the traffic control index in the `skb` structure. The `u16` value is required only when `use` is specified.

`dmac` DMAC

`smac` SMAC

Optional six byte destination or source MAC address to encode.

`type` TYPE

Optional 16-bit ethertype to encode. If not specified value of `0xED3E` will be used.

CONTROL

Action to take following an encode/decode.

index INDEX

Assign a unique ID to this action instead of letting the kernel choose one automatically. INDEX is a 32bit unsigned integer greater than zero.

EXAMPLES

On the receiving side, match packets with ethertype 0xdead and restart classification so that it will match ICMP on the next rule, at prio 3:

```
# tc qdisc add dev eth0 handle ffff: ingress
# tc filter add dev eth0 parent ffff: prio 2 protocol 0xdead \
    u32 match u32 0 0 flowid 1:1 \
    action ife decode reclassify
# tc filter add dev eth0 parent ffff: prio 3 protocol ip \
    u32 match ip protocol 0xff flowid 1:1 \
    action continue
```

Match with skb mark of 17:

```
# tc filter add dev eth0 parent ffff: prio 4 protocol ip \
    handle 0x11 fw flowid 1:1 \
    action ok
```

Configure the sending side to encode for the filters above. Use a destination IP address of 192.168.122.237/24, then tag with skb mark of decimal 17. Encode the packet with ethertype 0xdead, add skb->mark to whitelist of metadata to send, and rewrite the destination MAC address to 02:15:15:15:15:15.

```
# tc qdisc add dev eth0 root handle 1: prio
# tc filter add dev eth0 parent 1: protocol ip prio 10 u32 \
    match ip dst 192.168.122.237/24 \
    match ip protocol 1 0xff \
    flowid 1:2 \
    action skbedit mark 17 \
    action ife encode \
```

type 0xDEAD \

allow mark \

dst 02:15:15:15:15:15

SEE ALSO

tc(8), tc-u32(8)

iproute2

22 Apr 2016

IFE action in tc(8)