



Rocky Enterprise Linux 9.2 Manual Pages on command 'sane-xerox_mfp.5'

\$ man sane-xerox_mfp.5

sane-xerox_mfp(5) SANE Scanner Access Now Easy sane-xerox_mfp(5)

NAME

sane-xerox_mfp - SANE backend for Xerox Phaser 3200MFP device et al.

DESCRIPTION

The sane-xerox_mfp library implements a SANE (Scanner Access Now Easy) backend that provides access to several Samsung-based Samsung, Xerox, and Dell scanners. Please see full list of supported devices at <http://www.sane-project.org/sane-supported-devices.html>

CONFIGURATION

/etc/sane.d/xerox_mfp.conf

USB scanners do not need any configuration.

For SCX-4500W in network mode you need to specify

tcp host_address [port]

The `host_address` is passed through resolver, thus can be a dotted quad or a name from `/etc/hosts` or resolvable through DNS.

FILES

`/etc/sane.d/xerox_mfp.conf`

The backend configuration file. By default all scanner types/models are enabled, you may want to comment out unwanted entries.

`/usr/lib64/sane/libsane-xerox_mfp.a`

The static library implementing this backend.

`/usr/lib64/sane/libsane-xerox_mfp.so`

The shared library implementing this backend (present on systems that support dynamic loading).

ENVIRONMENT

`SANE_DEBUG_XEROX_MFP`

If the library was compiled with debug support enabled, this environment variable controls the debug level for this backend. Higher debug levels increase the verbosity of the output.

Example: `export SANE_DEBUG_XEROX_MFP=4`

LIMITATIONS

Multicast autoconfiguration for LAN scanners is not implemented yet. IPv6 addressing never been tested.

BUGS AND SUPPORT

If you have found a bug or need support please follow open-source way of acquiring support via mail-lists [http://www.sane-project.org/mail?](http://www.sane-project.org/mail?ing-lists.html)

[ing-lists.html](http://www.sane-project.org/mail?ing-lists.html) or [SANE bug tracker](http://www.sane-project.org/bug-tracker)

<http://www.sane-project.org/bugs.html>.

AUTHORS

Alex Belkin <abc@telekom.ru>.

Samsung SCX-4500W scan over network support by Alexander Kuznetsov
<acca(at)cpan.org>.

Color scanning on Samsung M2870 model and Xerox Cognac 3215 & 3225 models by Laxmeesh Onkar Markod <m.laxmeesh@samsung.com>.

SEE ALSO

sane(7), sane-usb(5)

15 Dec 2008

sane-xerox_mfp(5)