NAME

timerfd_create, timerfd_settime, timerfd_gettime – timers that notify via file descriptors

SYNOPSIS

#include <sys/timerfd.h>

int timerfd_create(int clockid, int flags);

int timerfd_gettime(int fd, struct itimerspec *curr_value);

DESCRIPTION

These system calls create and operate on a timer that delivers timer expiration notifications via a file descriptor. They provide an alternative to the use of **setitimer**(2) or **timer_create**(2), with the advantage that the file descriptor may be monitored by **select**(2), **poll**(2), and **epoll**(7).

The use of these three system calls is analogous to the use of timer_create(2), timer_settime(2), and timer_gettime(2). (There is no analog of timer_getoverrun(2), since that functionality is provided by read(2), as described below.)

timerfd_create()

timerfd_create() creates a new timer object, and returns a file descriptor that refers to that timer. The *clockid* argument specifies the clock that is used to mark the progress of the timer, and must be one of the following:

CLOCK_REALTIME

A settable system-wide real-time clock.

CLOCK_MONOTONIC

A nonsettable monotonically increasing clock that measures time from some unspecified point in the past that does not change after system startup.

CLOCK_BOOTTIME (Since Linux 3.15)

Like **CLOCK_MONOTONIC**, this is a monotonically increasing clock. However, whereas the **CLOCK_MONOTONIC** clock does not measure the time while a system is suspended, the **CLOCK_BOOTTIME** clock does include the time during which the system is suspended. This is useful for applications that need to be suspend-aware. **CLOCK_REALTIME** is not suitable for such applications, since that clock is affected by discontinuous changes to the system clock.

CLOCK_REALTIME_ALARM (since Linux 3.11)

This clock is like **CLOCK_REALTIME**, but will wake the system if it is suspended. The caller must have the **CAP_WAKE_ALARM** capability in order to set a timer against this clock.

CLOCK_BOOTTIME_ALARM (since Linux 3.11)

This clock is like **CLOCK_BOOTTIME**, but will wake the system if it is suspended. The caller must have the **CAP_WAKE_ALARM** capability in order to set a timer against this clock.

The current value of each of these clocks can be retrieved using **clock_gettime**(2).

Starting with Linux 2.6.27, the following values may be bitwise ORed in *flags* to change the behavior of **timerfd_create**():

TFD_NONBLOCK

Set the **O_NONBLOCK** file status flag on the open file description (see **open**(2)) referred to by the new file descriptor. Using this flag saves extra calls to **fcntl**(2) to achieve the same result.

TFD_CLOEXEC

Set the close-on-exec (**FD_CLOEXEC**) flag on the new file descriptor. See the description of the **O_CLOEXEC** flag in **open**(2) for reasons why this may be useful.

In Linux versions up to and including 2.6.26, *flags* must be specified as zero.

timerfd_settime()

timerfd_settime() arms (starts) or disarms (stops) the timer referred to by the file descriptor fd.

The *new_value* argument specifies the initial expiration and interval for the timer. The *itimerspec* structure used for this argument contains two fields, each of which is in turn a structure of type *timespec*:

```
struct timespec {
   time_t tv_sec; /* Seconds */
   long tv_nsec; /* Nanoseconds */
};
struct itimerspec {
   struct timespec it_interval; /* Interval for periodic timer */
   struct timespec it_value; /* Initial expiration */
};
```

new_value.it_value specifies the initial expiration of the timer, in seconds and nanoseconds. Setting either field of *new_value.it_value* to a nonzero value arms the timer. Setting both fields of *new_value.it_value* to zero disarms the timer.

Setting one or both fields of *new_value.it_interval* to nonzero values specifies the period, in seconds and nanoseconds, for repeated timer expirations after the initial expiration. If both fields of *new_value.it_interval* are zero, the timer expires just once, at the time specified by *new_value.it_value*.

By default, the initial expiration time specified in *new_value* is interpreted relative to the current time on the timer's clock at the time of the call (i.e., *new_value.it_value* specifies a time relative to the current value of the clock specified by *clockid*). An absolute timeout can be selected via the *flags* argument.

The *flags* argument is a bit mask that can include the following values:

TFD_TIMER_ABSTIME

Interpret *new_value.it_value* as an absolute value on the timer's clock. The timer will expire when the value of the timer's clock reaches the value specified in *new_value.it_value*.

TFD_TIMER_CANCEL_ON_SET

If this flag is specified along with **TFD_TIMER_ABSTIME** and the clock for this timer is **CLOCK_REALTIME** or **CLOCK_REALTIME_ALARM**, then mark this timer as cancelable if the real-time clock undergoes a discontinuous change (**settimeofday**(2), **clock_settime**(2), or similar). When such changes occur, a current or future **read**(2) from the file descriptor will fail with the error **ECANCELED**.

If the *old_value* argument is not NULL, then the *itimerspec* structure that it points to is used to return the setting of the timer that was current at the time of the call; see the description of **timerfd_gettime**() following.

timerfd_gettime()

timerfd_gettime() returns, in *curr_value*, an *itimerspec* structure that contains the current setting of the timer referred to by the file descriptor fd.

The *it_value* field returns the amount of time until the timer will next expire. If both fields of this structure are zero, then the timer is currently disarmed. This field always contains a relative value, regardless of whether the **TFD_TIMER_ABSTIME** flag was specified when setting the timer.

The *it_interval* field returns the interval of the timer. If both fields of this structure are zero, then the timer is set to expire just once, at the time specified by *curr_value.it_value*.

Operating on a timer file descriptor

The file descriptor returned by **timerfd_create()** supports the following operations:

read(2) If the timer has already expired one or more times since its settings were last modified using timerfd_settime(), or since the last successful read(2), then the buffer given to read(2) returns an unsigned 8-byte integer (*uint64_t*) containing the number of expirations that have occurred. (The returned value is in host byte order—that is, the native byte order for integers on the host

machine.)

If no timer expirations have occurred at the time of the **read**(2), then the call either blocks until the next timer expiration, or fails with the error **EAGAIN** if the file descriptor has been made nonblocking (via the use of the **fcntl**(2) **F_SETFL** operation to set the **O_NONBLOCK** flag).

A read(2) fails with the error EINVAL if the size of the supplied buffer is less than 8 bytes.

If the associated clock is either CLOCK_REALTIME or CLOCK_REALTIME_ALARM, the timer is absolute (TFD_TIMER_ABSTIME), and the flag TFD_TIMER_CANCEL_ON_SET was specified when calling timerfd_settime(), then read(2) fails with the error ECANCELED if the real-time clock undergoes a discontinuous change. (This allows the reading application to discover such discontinuous changes to the clock.)

poll(2), select(2) (and similar)

The file descriptor is readable (the **select**(2) *readfds* argument; the **poll**(2) **POLLIN** flag) if one or more timer expirations have occurred.

The file descriptor also supports the other file-descriptor multiplexing APIs: **pselect**(2), **ppoll**(2), and **epoll**(7).

ioctl(2) The following timerfd-specific command is supported:

TFD_IOC_SET_TICKS (since Linux 3.17)

Adjust the number of timer expirations that have occurred. The argument is a pointer to a nonzero 8-byte integer ($uint64_t^*$) containing the new number of expirations. Once the number is set, any waiter on the timer is woken up. The only purpose of this command is to restore the expirations for the purpose of checkpoint/restore. This operation is available only if the kernel was configured with the **CONFIG_CHECKPOINT_RESTORE** option.

close(2)

When the file descriptor is no longer required it should be closed. When all file descriptors associated with the same timer object have been closed, the timer is disarmed and its resources are freed by the kernel.

fork(2) semantics

After a **fork**(2), the child inherits a copy of the file descriptor created by **timerfd_create**(). The file descriptor refers to the same underlying timer object as the corresponding file descriptor in the parent, and **read**(2)s in the child will return information about expirations of the timer.

execve(2) semantics

A file descriptor created by **timerfd_create**() is preserved across **execve**(2), and continues to generate timer expirations if the timer was armed.

RETURN VALUE

On success, **timerfd_create**() returns a new file descriptor. On error, -1 is returned and *errno* is set to indicate the error.

timerfd_settime() and **timerfd_gettime**() return 0 on success; on error they return -1, and set *errno* to indicate the error.

ERRORS

timerfd_create() can fail with the following errors:

EINVAL

The *clockid* argument is neither **CLOCK_MONOTONIC** nor **CLOCK_REALTIME**;

EINVAL

flags is invalid; or, in Linux 2.6.26 or earlier, flags is nonzero.

EMFILE

The per-process limit on the number of open file descriptors has been reached.

ENFILE

The system-wide limit on the total number of open files has been reached.

ENODEV

Could not mount (internal) anonymous inode device.

ENOMEM

There was insufficient kernel memory to create the timer.

timerfd_settime() and timerfd_gettime() can fail with the following errors:

EBADF

fd is not a valid file descriptor.

EFAULT

new_value, old_value, or curr_value is not valid a pointer.

EINVAL

fd is not a valid timerfd file descriptor.

timerfd_settime() can also fail with the following errors:

EINVAL

new_value is not properly initialized (one of the *tv_nsec* falls outside the range zero to 999,999,999).

EINVAL

flags is invalid.

VERSIONS

These system calls are available on Linux since kernel 2.6.25. Library support is provided by glibc since version 2.8.

CONFORMING TO

These system calls are Linux-specific.

BUGS

Currently, **timerfd_create**() supports fewer types of clock IDs than **timer_create**(2).

EXAMPLE

The following program creates a timer and then monitors its progress. The program accepts up to three command-line arguments. The first argument specifies the number of seconds for the initial expiration of the timer. The second argument specifies the interval for the timer, in seconds. The third argument specifies the number of times the program should allow the timer to expire before terminating. The second and third command-line arguments are optional.

The following shell session demonstrates the use of the program:

```
$ a.out 3 1 100
0.000: timer started
3.000: read: 1; total=1
4.000: read: 1; total=2
^z
                   # type control-Z to suspend the program
[1]+ Stopped
                            ./timerfd3_demo 3 1 100
                   # Resume execution after a few seconds
$ fq
a.out 3 1 100
9.660: read: 5; total=7
10.000: read: 1; total=8
11.000: read: 1; total=9
^C
                    # type control-C to suspend the program
```

Program source

#include <sys/timerfd.h>

TIMERFD_CREATE(2)

```
#include <time.h>
#include <unistd.h>
#include <stdlib.h>
#include <stdio.h>
#include <stdint.h> /* Definition of uint64_t */
#define handle_error(msg) \
        do { perror(msg); exit(EXIT_FAILURE); } while (0)
static void
print_elapsed_time(void)
{
    static struct timespec start;
    struct timespec curr;
    static int first_call = 1;
    int secs, nsecs;
    if (first_call) {
        first_call = 0;
        if (clock_gettime(CLOCK_MONOTONIC, &start) == -1)
           handle_error("clock_gettime");
    }
    if (clock_gettime(CLOCK_MONOTONIC, &curr) == -1)
        handle_error("clock_gettime");
    secs = curr.tv_sec - start.tv_sec;
    nsecs = curr.tv_nsec - start.tv_nsec;
    if (nsecs < 0) {
       secs--;
       nsecs += 100000000;
    }
   printf("%d.%03d: ", secs, (nsecs + 500000) / 1000000);
}
int
main(int argc, char *argv[])
{
    struct itimerspec new_value;
    int max_exp, fd;
    struct timespec now;
    uint64_t exp, tot_exp;
    ssize_t s;
    if ((argc != 2) && (argc != 4)) {
       fprintf(stderr, "%s init-secs [interval-secs max-exp]\n",
                argv[0]);
        exit(EXIT_FAILURE);
    }
    if (clock_gettime(CLOCK_REALTIME, &now) == -1)
        handle_error("clock_gettime");
```

```
/* Create a CLOCK_REALTIME absolute timer with initial
```

```
expiration and interval as specified in command line */
new_value.it_value.tv_sec = now.tv_sec + atoi(argv[1]);
new_value.it_value.tv_nsec = now.tv_nsec;
if (argc == 2) {
    new_value.it_interval.tv_sec = 0;
    max_exp = 1;
} else {
   new_value.it_interval.tv_sec = atoi(argv[2]);
    max_exp = atoi(argv[3]);
}
new_value.it_interval.tv_nsec = 0;
fd = timerfd_create(CLOCK_REALTIME, 0);
if (fd == -1)
    handle_error("timerfd_create");
if (timerfd_settime(fd, TFD_TIMER_ABSTIME, &new_value, NULL) == -1)
    handle_error("timerfd_settime");
print_elapsed_time();
printf("timer started\n");
for (tot_exp = 0; tot_exp < max_exp;) {</pre>
    s = read(fd, &exp, sizeof(uint64_t));
    if (s != sizeof(uint64_t))
       handle_error("read");
    tot_exp += exp;
    print_elapsed_time();
    printf("read: %llu; total=%llu\n",
            (unsigned long long) exp,
            (unsigned long long) tot_exp);
}
exit(EXIT_SUCCESS);
```

SEE ALSO

}

eventfd(2), poll(2), read(2), select(2), setitimer(2), signalfd(2), timer_create(2), timer_gettime(2), timer_settime(2), epoll(7), time(7)

COLOPHON

This page is part of release 5.05 of the Linux *man-pages* project. A description of the project, information about reporting bugs, and the latest version of this page, can be found at https://www.kernel.org/doc/man-pages/.