

NAME

tipc-node – modify and show local node parameters or list peer nodes

SYNOPSIS

tipc node set { **address** *ADDRESS* | **netid** *NETID* }

tipc node get { **address** | **netid** }

tipc node list

OPTIONS

Options (flags) that can be passed anywhere in the command chain.

-h, --help

Show help about last valid command. For example **tipc node --help** will show node help and **tipc --help** will show general help. The position of the option in the string is irrelevant.

DESCRIPTION**Node parameters****address**

The TIPC logical address. On the form x.y.z where x, y and z are unsigned integers.

netid

Network identity. Can be used to create individual TIPC clusters on the same media.

EXIT STATUS

Exit status is 0 if command was successful or a positive integer upon failure.

SEE ALSO

tipc(8), **tipc-bearer(8)**, **tipc-link(8)**, **tipc-media(8)**, **tipc-nametable(8)**, **tipc-peer(8)**, **tipc-socket(8)**

REPORTING BUGS

Report any bugs to the Network Developers mailing list <netdev@vger.kernel.org> where the development and maintenance is primarily done. You do not have to be subscribed to the list to send a message there.

AUTHOR

Richard Alpe <richard.alpe@ericsson.com>